



Fast-acting, pilot-operated, balanced piston relief cartridges are normally closed, pressure-limiting valves used to protect hydraulics components from pressure transients. Fast opening and closing is gained at the expense of smoothness. When the pressure at the inlet (port 1) reaches the valve setting, the valve starts to open to tank (port 2), throttling flow to limit the pressure rise. These valves have low pressure rise vs. flow and are very fast.

TECHNICAL DATA

NOTE: DATA MAY VARY BY CONFIGURATION. SEE CONFIGURATION SECTION.

| | |
|--|-------------------------|
| Factory Pressure Settings Established at | 15 L/min. |
| Maximum Operating Pressure | 350 bar |
| Maximum Valve Leakage at 110 SUS (24 cSt) | 30 cc/min.@70 bar |
| Response Time - Typical | 2 ms |
| Adjustment - No. of CW Turns from Min. to Max. setting | 5 |
| Locknut Hex Size | 15 mm |
| Locknut Torque | 9 - 10 Nm |
| Seal kit - Cartridge | Buna: 990010007 |
| Seal kit - Cartridge | Polyurethane: 990010002 |
| Seal kit - Cartridge | Viton: 990010006 |

NOTES

For Series 1 cartridges configured with an O control (panel mount handknob), a .75 in. (19 mm) diameter hole is required in the panel.

CONFIGURATION OPTIONS

Model Code Example: RPEELAN

| CONTROL | (L) ADJUSTMENT RANGE | (A) SEAL MATERIAL | (N) MATERIAL/COATING |
|---|--|-------------------|---------------------------------|
| L Standard Screw Adjustment | A 100 - 3000 psi (7 - 210 bar), 1000 psi (70 bar) Standard Setting | N Buna-N | Standard Material/Coating |
| C Tamper Resistant - Factory Set | B 50 - 1500 psi (3,5 - 105 bar), 1000 psi (70 bar) Standard Setting | V Viton | /AP Stainless Steel, Passivated |
| K Handknob | C 150 - 6000 psi (10,5 - 420 bar), 1000 psi (70 bar) Standard Setting | | /LH Mild Steel, Zinc-Nickel |
| O Handknob with Panel Mount | D 25 - 800 psi (1,7 - 55 bar), 400 psi (28 bar) Standard Setting | | |
| Y Tri-Grip Handknob | E 25 - 400 psi (1,7 - 28 bar), 200 psi (14 bar) Standard Setting | | |
| | W 150 - 4500 psi (10,5 - 315 bar), 1000 psi (70 bar) Standard Setting | | |